

**B10 AC Bell**

**Features**

- UL listed. ULC, CSFM, and FM pending.
- Complies with OSHA 29,Part 1910.165
- High sound output with low current draw
- 10" shell size @ 115VAC
- Integral RFI suppression minimizes induced noise on alarm lines
- Semi-flush mounting to standard 4" square backboxes or surface mounting to Siemens surface backboxes
- Polarized for supervision of alarm lines with screw terminal inputs for fast and secure in-out field wiring of #12 to #18 AWG wire
- Attractive textured finish to enhance appearance and durability
- For combined audible (bell) and visual signaling, convenient retrofit assemblies (Series ST) are available with Multi-Candela strobes.



**10-INCH BELLS**

**Description**

This bell is offered in the 10" size at 115VAC for both indoor and outdoor installations.

This model provides high sound output with low power consumption, and is provided with screw terminal inputs for secure in-out field wiring.

square backboxes or surface mount to Siemens indoor BBS backbox or outdoor WBBS backbox. All bells shall be polarized for line supervision and shall have screw terminals for in-out field wiring. The finish on all models shall be textured enamel. All notification appliances shall be listed for "Special Applications".

**Engineering Specifications**

The alarm signals shall be Siemens Series B10 Bells or approved equal. They shall be UL Listed for Fire Protective Service. Sound output at 10 feet shall range up to 85 dBA. The bells shall semi-flush mount to standard 4"

**Technical Information**

For complete technical information, please consult the relevant installation sheets as well as the Siemens Compatibility Guide.

**Ordering Information / Mounting Requirements / Approvals**

Model Number	Order Code	Shell Size	Mounting Options*	Agency Approvals			
				UL	ULC	CSFM	FM
B10-115-R	500-636001	10	D,E,J,K,P,R,S	X	#	#	#

X = listed/approved      # = pending      \* = Refer to Data Sheet #9675 for mounting options.

1. Typical dBA at 10 feet is measured in an anechoic chamber.
2. All models are provided with in-out screw terminals.
3. Each bell mechanism is adjusted to operate only with the shell provided
4. Do not mix shells and mechanisms during installation.

**WARNING:** PLEASE READ THESE SPECIFICATIONS AND INSTALLATION INSTRUCTIONS CAREFULLY BEFORE USING, SPECIFYING OR APPLYING THIS PRODUCT. FAILURE TO COMPLY WITH ANY OF THESE INSTRUCTIONS, CAUTIONS AND WARNINGS COULD RESULT IN IMPROPER APPLICATION, INSTALLATION AND/OR OPERATION OF THESE PRODUCTS IN AN EMERGENCY SITUATION, WHICH COULD RESULT IN PROPERTY DAMAGE, AND SERIOUS INJURY OR DEATH TO YOU AND/OR OTHERS.

 **FARADAY**

Siemens Building Technologies, Inc.  
8 Fernwood Road • Florham Park, NJ 07932  
Tel: (973) 593-2600 • Fax: (973) 593-6670  
Web: [www.faradayfirealarms.com](http://www.faradayfirealarms.com)