

Model RPR-100 Serial Dot Matrix Printer

Features

- UL listed, EDP as an ancillary device
- Compact design
- Uses standard 9" x 11" folded tractor/pin feed paper
- Serial drive card included
- Prints in 80 column format @ 10 OPT
- 24 CPS print speed
- 9 pin serial dot matrix print head
- Quiet 57 db operation
- Full (1) year warranty

Description

In situations requiring a printed hard copy of all system events and restorations in an 80 column format, the RPR-100 Remote Printer may be used. The RPR-100 printer should be located no more than 50 ft. max. wiring distance from the attached Fire Alarm Control Unit. In all cases this should leave the RPR-100 within the same physical space or room as the Control Unit. The RPR-100 is suitable for table top or shelf mounting and should be located in a secure area to discourage tampering or record theft. If remote printer operation is required during a primary power failure condition, the use of a separate UL listed interruptible Power Supply (UPS) source must be supplied to the unit. The RPR-100 remote printer is to be used as an ancillary event record device only.

Specifications

Print Method:

9-pin Serial Impact Dot Matrix

Print Speed:

Utility: 200 CPS
Draft: 240 CPS @ 10 and 171 CPI &
300 CPS @ 12 CPI
NLQ: 50 CPS

Print Format:

80 CPL @ 10 CPI

Interface:

Serial



Model RPR-100

Front Panel:

Select, Form Feed, Line Feed, Top of Form & Print Mode

Paper Handling:

Continuous Pin Feed

Number of Copies:

Original plus 4

Paper Thickness:

.014" max. (0.35mm)

Paper Weight:

16 to 20 lb.

Printhead Life:

2000,000,000 Characters avg.

Ribbon Life:

3,000,000 Characters

Size:

14.2" (36cm) W x 10.8" (27.5cm) D x 3.2" (8cm) H

Weight:

10 lbs.

Noise:

57 db

Input Power:

120 VAC @ 50/60 Hz.

Current Draw:

40 VA on / 8 VA idle, 35W

Environmental:

40°F (5°C) to 104°F (40°C) @ 5 to 80% RH

Listings:

UL478 / CSA C22.2(220) / FCC Class B

Ordering Information

Model	Description	Part No.
RPR-100	(ML 184T) Remote serial printer	500-699645FA



Siemens Building Technologies, Inc.
8 Fernwood Road • Florham Park, NJ 07932
Tel: (973) 593-2600 • Fax: (973) 593-6670
Web: www.faradayllc.com

WARNING - The information contained in this document is intended only as a summary and is subject to change without notice. The devices described in this document have specific instruction sheets which cover various technical, limitation and liability information. Copies of these instruction sheets and the General Product Warning and Limitations Document, which also contains important information, are provided with the product and are available from the Manufacturer. Information contained in these documents should be consulted before specifying or using the product. For further information or assistance concerning particular problems contact the Manufacturer.